



Occhio air module datasheet

Bluetooth dimmer module for trailing-edge phase cut dimmable luminaires and power supply units; mounting in cavity box or light switch. Maximum ease of use and total control via Bluetooth low energy. Switching and dimming of individual luminaires, groups and scenes.



Dimensions in mm

technical data Occhio air module

properties	material	plastic
	weight	15 g
surface	module	glossy white
electricity	transmission technology	Bluetooth Low Energy
	connection	85–240 V AC, 50–60 Hz
	range (environment-dependent)	up to 50 m (indoor), up to 200 m (outdoor)
	recommended cable cross section	0,5–1,5 mm ²
	max. power (@ 230 V AC)	LED max. 3 × 26 W with Occhio converter, HV halogen or HV LED max. 100 W, LV halogen max. 100 W
	no-load standby power	< 0,3 W
	permitted operating conditions	max. 30°C for indoor use only

mounting options Occhio air module

